		Technology	Housing Ø [mm]	Supply voltage [V]	Output signal	Number of outputs	Angle el. [°]	Mounting	Output Connection
	**CP-2HX**	Contacless, Hall	40	5	10 to 90% Vin, PWM	2	90, 180, 360	Flange	Stecker
	**CP-1HX**	Contactless, Hall	28 x 14	4.5...5.5	Ratiometric, PWM	1, 2	50° up to 360°	Flange	Wire
	**CP-45F**	Resistive	45	0...15	0 to 100% Vin	1, 2	350	Servo Ø45	Solder tab
	**CP-45FRBN**	Resistive	67	0...15	0 to 100% Vin	1	350	Flange Ø66	Stecker
	**CP-2FL**	Resistive	22.3	0...15	0 to 100% Vin	1	340	Bushing M9	Wire
	**12A M MPB**	Contactless, Hall	12	5 V +/- 10%	0 to 5 V DC Ratiometric	1	0 to 360 programmable	Bushing - 1 hole	Cable, terminal block
	**12x M MPB**	Contactless, Hall	12	5 V +/- 10%, 3.3 V +/- 10%	0 to 5 V DC Ratiometric, I2C, Absolute SPI, SENT, PWM	1	0 to 360 programmable	Bushing - 1 hole	Cable, terminal block
	**CP-22H-xS**	Contacless, Hall	22 x 30	5	10 to 90% Vin	1, 2	1800 to 21600	Flange	wire

		Technology	Housing Ø [mm]	Supply voltage [V]	Output signal	Number of outputs	Angle el. [°]	Mounting	Output Connection
	**HP-18**	Resistive	22.3	0...40	0 to 100% Vin	1	3600	Bushing M9	Wire
	**CP-2FK(b)J**	Resistive	22.3	0...15	0 to 100% Vin	1	340	Servo Ø22.3	Solder Pin
	**CP-2FK(m)J**	Resistive	22.3	0...15	0 to 100% Vin	1	340	Servo Ø22.3	Solder Pin
	**CP-2FB(b)J**	Resistive	22.3	0...15	0 to 100% Vin	1	340	Bushing M9	Solder Pin
	**CP-2FB(m)J**	Resistive	22.3	0...15	0 to 100% Vin	1	340	Bushing M9	Solder Pin
	**CP-2FBJ-6**	Resistive	22.3	0...15	0 to 100% Vin	1	340	Bushing M9	Solder Pin
	**CP-16U**	Contactless, magneto resistive	16	3...5.5	30 to 70% Vin	1	90	Bushing M9	Wire
	**CP36U**	Contactless, magneto resistive	36	16 - 32	4 to 20 mA	1	18 ... 360	Flange	Wire



		Technology	Housing Ø [mm]	Supply voltage [V]	Output signal	Number of outputs	Angle el. [°]	Mounting	Output Connection
	**CP-16U-1**	Contactless, magneto resistive	16	3...5.5	30 to 70% Vin	1	120	Bushing M9	Wire
	**UV-JHA**	Contacless, Hall	27	5	0 to 5 V DC Ratiometric	1	80	Flange	Wire
	**CP-20H**	Contacless, Hall	22	5	0 to 5 V DC Ratiometric	1, 2	270, 300, 340, 359	Bushing M9	Wire
	**CP-45H**	Contacless, Hall	45	5	0 to 5 V DC Ratiometric	1, 2	90 to 360	Servoflange	Wire
	**CP-45H-5V**	Contacless, Hall	45	8...32	0 to 5 V DC	1, 2	90 to 360	Servoflange	Wire
	**CP-45H-10V**	Contacless, Hall	45	14...32	0 to 10 V DC	1, 2	90 to 360	Servoflange	Wire
	**CP-45H-A**	Contacless, Hall	45	20...28	4 to 20 mA	1, 2	90 to 360	Servoflange	Wire
	**CP-2HA**	Contacless, Hall	28	5	0 to 5 V DC Ratiometric	1, 2	100, 200, 350	Flange	Wire



		Technology	Housing Ø [mm]	Supply voltage [V]	Output signal	Number of outputs	Angle el. [°]	Mounting	Output Connection
	**CP-3HABS**	Contacless, Hall	20	5	0 to 5 V DC Ratiometric	1, 2	60, 90	Flange	Wire
	**CP-2UKN-A**	Contactless, magneto resistive	36	20...28	4 to 20 mA	1	90	Flange	Cable
	**CP-2HK-10R**	Contacless, Hall	36	10	10% to 90%Vin	1	80, 270, 300, 360	Flange	Cable
	**CP-2HK-8R**	Contacless, Hall	36	8	10% to 90%Vin	1	80, 270, 300, 360	Flange	Cable
	**CP-2HK**	Contacless, Hall	36	5	0 to 5 V DC Ratiometric	1	80, 270, 300, 360	Flange	Cable
	**CP-2UN**	Contactless, magneto resistive	16	0...10	40% to 60%Vin	1	90	Bushing M9	Wire
	**CP-2UTN**	Contactless, magneto resistive	16	0...10	40% to 60%Vin	1	90	Bushing M9	Solder Pin
	**CP-2UPN-50**	Contactless, magneto resistive	16	0...10	40% to 60%Vin	1	90	Flange	Solder Pin


		Technology	Housing Ø [mm]	Supply voltage [V]	Output signal	Number of outputs	Angle el. [°]	Mounting	Output Connection
	**MA3**	Contacless, Hall	12.2	5	0 to 5 V DC, PWM	1	360	Bushing	Miniature connector
	**MAE3**	Contacless, Hall	12.2	5	0 to 5 V DC, PWM	1	360	Flange	Miniature connector
	**CP-45H-10S**	Contacless, Hall	61	5	0 to 5 V DC Ratiometric	1	3500	Flange	Terminal Block
	**CP-3HK-100**	Contacless, Hall	36	5	0 to 5 V DC Ratiometric	1	360	Flange	Cable
	**QP-3HB**	Contacless, Hall	21	5	0 to 5 V DC Ratiometric	1, 1	10, 20, 60, 90, 120	Flange	Wire
	**QP-3HBB**	Contacless, Hall	21	6	0 to 5 V DC Ratiometric	1, 2	91	Flange	Wire
	**CP-30H**	Contacless, Hall	28	5	0 to 5 V DC Ratiometric	1	60		Wire
	**QP-2H**	Contacless, Hall	15	5	0 to 5 V DC Ratiometric	1	90	Bushing M9	Wire


		Technology	Housing Ø [mm]	Supply voltage [V]	Output signal	Number of outputs	Angle el. [°]	Mounting	Output Connection
	**CP-2HB**	Contacless, Hall	16	5	0 to 5 V DC Ratiometric	1	90	Bushing M10	Solder Pin
	**CP-2FCB(m)**	Resistive	22.3	0...15	0 to 100% Vin	1	340	Bushing M9	Miniature connector
	**CP-2FC-6**	Resistive	22.3	0...15	0 to 100% Vin	1	340	Bushing M9	Miniature connector
	**CP-2FABSJ**	Resistive	28	0...15	0 to 100% Vin	1, 2	90	Flange	Wire
	**CP-2FABSJ-09**	Resistive	28	0...15	0 to 100% Vin	1	90	Flange	Wire
	**CP-2FABSJ-128**	Resistive	28	0...15	0 to 100% Vin	1	340	Flange	Wire
	**QP-3F**	Resistive	29	0...15	0 to 100% Vin	1	90	Flange	Wire
	**CP-5S**	Resistive	52	0...200	0 to 100% Vin	1	355	Servo Ø47.6	Solder Pin



		Technology	Housing Ø [mm]	Supply voltage [V]	Output signal	Number of outputs	Angle el. [°]	Mounting	Output Connection
	**CP-2F-xxSRB**	Resistive	30	0...15	0 to 100% Vin	1	3400 to 18000	Flange	Solder Pin
	**CP-2FWP-10S**	Resistive	30	0...15	0 to 100% Vin	1	3400, 34000	Flange	Solder Pin
	**CP-45F-xxSX**	Resistive	61	0...15	0 to 100% Vin	1	3500, 350'000		Terminal Block
	**CPP-60**	Resistive	61	0...15	0 to 100% Vin	1	355	Servo Ø62	Solder Pin
	**25_30A PPB S0505 2C**								
	**25_30A PP B S2410**	Contactless, Hall	25, 30	15 - 30 V	0 to 10 V DC	1	0 to 360 programmable	Bushing - 1 hole	Cable, miniature connector, terminal block
	**25_30A PP B S2442**	Contactless, Hall	25, 30	15 - 30 V	4 to 20 mA	1	0 to 360 programmable	Bushing - 1 hole	Cable, miniature connector, terminal block
	**25_30A PP B S0505**	Contactless, Hall	25, 30	5 V +/- 10%	0 to 5 V DC Ratiometric	1	0 to 360 programmable	Bushing - 1 hole	Cable, miniature connector, terminal block

		Technology	Housing Ø [mm]	Supply voltage [V]	Output signal	Number of outputs	Angle el. [°]	Mounting	Output Connection
	**25_30A PP F S2410**	Contactless, Hall	25, 30	15 - 30 V	0 to 10 V DC	1	0 to 360 programmable	Flange - 2 screws	Cable, miniature connector, terminal block
	**25_30A PP F 2442**	Contactless, Hall	25, 30	15 - 30 V	4 to 20 mA	1	0 to 360 programmable	Flange - 2 screws	Cable, miniature connector, terminal block
	**25_30A PP F S0505 2C**	Contactless, Hall	25, 30	5 V +/- 10%	0 to 5 V DC Ratiometric	2	0 to 360 programmable	Flange - 2 screws	Cable, miniature connector, terminal block
	**25_30A PP K S0505**	Contactless, Hall	25, 30	5 V +/- 10%	0 to 5 V DC Ratiometric	1	0 to 360 programmable	Kit - no shaft - 2 screw	Cable, miniature connector, terminal block
	**25_30A PP K S2410**	Contactless, Hall	25, 30	15 - 30 V	0 to 10 V DC	1	0 to 360 programmable	Kit - no shaft - 2 screw	Cable, miniature connector, terminal block
	**25_30A PP K S2442**	Contactless, Hall	25, 30	15 - 30 V	4 to 20 mA	1	0 to 360 programmable	Kit - no shaft - 2 screw	Cable, miniature connector, terminal block
	**25_30A PP K S0505 2C**	Contactless, Hall	25, 30	5 V +/- 10%	0 to 5 V DC Ratiometric	2	0 to 360 programmable	Kit - no shaft - 2 screw	Cable, miniature connector, terminal block
	**25_30I PP B S05OC MT**	Contactless, Hall	25, 30	5 V +/- 10%	Incremental 5 V Op.Col.	1	0 to 360 programmable	Bushing - 1 hole	Cable, miniature connector, terminal block



		Technology	Housing Ø [mm]	Supply voltage [V]	Output signal	Number of outputs	Angle el. [°]	Mounting	Output Connection
	**25_30I PP B S24OC MT**	Contactless, Hall	25, 30	9 - 30 V	Incremental 24 V Op.Col.	1	0 to 360 programmable	Bushing - 1 hole	Cable, miniature connector, terminal block
	**25_30I PP B S05TTL MT**	Contactless, Hall	25, 30	5 V +/- 10%	Incremental 5 V TTL	1	0 to 360 programmable	Bushing - 1 hole	Cable, miniature connector, terminal block
	**25_30I PP F S05OC**	Contactless, Hall	25, 30	5 V +/- 10%	Incremental 5 V Op.Col.	1	0 to 360 programmable	Flange - 2 screws	Cable, miniature connector, terminal block
	**25_30I PP F S24OC**	Contactless, Hall	25, 30	9 - 30 V	Incremental 24 V Op.Col.	1	0 to 360 programmable	Flange - 2 screws	Cable, miniature connector, terminal block
	**25_30I PP F S05TTL**	Contactless, Hall	25, 30	5 V +/- 10%	Incremental 5 V TTL	1	0 to 360 programmable	Flange - 2 screws	Cable, miniature connector, terminal block
	**25_30I PP K 05OC**	Contactless, Hall	25, 30	5 V +/- 10%	Incremental 5 V Op.Col.	1	0 to 360 programmable	Kit - no shaft - 2 screw	Cable, miniature connector, terminal block
	**25_30I PP K S24OC**	Contactless, Hall	25, 30	9 - 30 V	Incremental 24 V Op.Col.	1	0 to 360 programmable	Kit - no shaft - 2 screw	Cable, miniature connector, terminal block
	**25_30I PP K S05TTL**	Contactless, Hall	25, 30	5 V +/- 10%	Incremental 5 V TTL	1	0 to 360 programmable	Kit - no shaft - 2 screw	Cable, miniature connector, terminal block




		Technology	Housing Ø [mm]	Supply voltage [V]	Output signal	Number of outputs	Angle el. [°]	Mounting	Output Connection
	**25_30P PP B 05SPI MT**	Contactless, Hall	25, 30	5 V +/- 10%	Absolute SPI	1	0 to 360 programmable	Bushing - 1 hole	Cable, miniature connector, terminal block
	**25_30P PP B 05SPI 2C MT**	Contactless, Hall	25, 30	5 V +/- 10%	Absolute SPI	2	0 to 360 programmable	Bushing - 1 hole	Cable, miniature connector, terminal block
	**25_30P PP F 05SPI**	Contactless, Hall	25, 30	5 V +/- 10%	Absolute SPI	1	0 to 360 programmable	Flange - 2 screws	Cable, miniature connector, terminal block
	**25_30P PP F 05SPI 2C**	Contactless, Hall	25, 30	5 V +/- 10%	Absolute SPI	2	0 to 360 programmable	Flange - 2 screws	Cable, miniature connector, terminal block
	**25_30P PP K 05SPI**	Contactless, Hall	25, 30	5 V +/- 10%	Absolute SPI	1	0 to 360 programmable	Kit - no shaft - 2 screw	Cable, miniature connector, terminal block
	**25_30P PP K 05SPI 2C**	Contactless, Hall	25, 30	5 V +/- 10%	Absolute SPI	2	0 to 360 programmable	Kit - no shaft - 2 screw	Cable, miniature connector, terminal block
	**25_30Y PP B 05SSI MT**	Contactless, Hall	25, 30	5 V +/- 10%	5 V SSI	1	0 to 360 programmable	Bushing - 1 hole	Cable, miniature connector, terminal block
	**25_30Y PP B 24SSI MT**	Contactless, Hall	25, 30	9 - 30 V	24 V SSI	1	0 to 360 programmable	Bushing - 1 hole	Cable, miniature connector, terminal block



		Technology	Housing Ø [mm]	Supply voltage [V]	Output signal	Number of outputs	Angle el. [°]	Mounting	Output Connection
	**25_30Y BB F 05SSI**	Contactless, Hall	25, 30	5 V +/- 10%	5 V SSI	1	0 to 360 programmable	Flange - 2 screws	Cable, miniature connector, terminal block
	**25_30Y BB F 24SSI**	Contactless, Hall	25, 30	9 - 30 V	24 V SSI	1	0 to 360 programmable	Flange - 2 screws	Cable, miniature connector, terminal block
	**25_30Y PP K 05SSI**	Contactless, Hall	25, 30	5 V +/- 10%	5 V SSI	1	0 to 360 programmable	Kit - no shaft - 2 screw	Cable, miniature connector, terminal block
	**25_30Y PP K 24SSI**	Contactless, Hall	25, 30	9 - 30 V	24 V SSI	1	0 to 360 programmable	Kit - no shaft - 2 screw	Cable, miniature connector, terminal block
	**22A PBB S0505**	Contactless, Hall	22	5 V +/- 10%	0 to 5 V DC Ratiometric	1	0 to 360 programmable	Bushing - 1 hole	Cable, terminal block
	**22A EPPB S0505**	Contactless, Hall	22	5 V +/- 10%	0 to 5 V DC Ratiometric	1	0 to 360 programmable	Bushing - 1 hole	Cable, terminal block
	**22A PBB S2410**	Contactless, Hall	22	15 - 30 V	0 to 10 V DC	1	0 to 360 programmable	Bushing - 1 hole	Cable, terminal block
	**22A PBBL 2442**	Contactless, Hall	22	15 - 30 V	4 to 20 mA	1	0 to 360 programmable	Bushing - 1 hole	Cable, terminal block

		Technology	Housing Ø [mm]	Supply voltage [V]	Output signal	Number of outputs	Angle el. [°]	Mounting	Output Connection
	**22A PBBL S0505 2C**	Contactless, Hall	22	5 V +/- 10%	0 to 5 V DC Ratiometric	2	0 to 360 programmable	Bushing - 1 hole	Cable, terminal block
	**36A PBSL S0505**	Contactless, Hall	36	5 V +/- 10%	0 to 5 V DC Ratiometric	1	0 to 360 programmable	3 mounting screws	Solder pin, cable, miniature connector, terminal block
	**36A PBSL S2410**	Contactless, Hall	36	15 - 30 V	0 to 10 V DC	1	0 to 360 programmable	3 mounting screws	Solder pin, cable, miniature connector, terminal block
	**36A PBSL S2442**	Contactless, Hall	36	15 - 30 V	4 to 20 mA	1	0 to 360 programmable	3 mounting screws	Solder pin, cable, miniature connector, terminal block
	**36A PBSL S0505 2C**	Contactless, Hall	36	5 V +/- 10%	0 to 5 V DC Ratiometric	2	0 to 360 programmable	3 mounting screws	Solder pin, cable, miniature connector, terminal block
	**50A PBSL S0505**	Contactless, Hall	50	5 V +/- 10%	0 to 5 V DC Ratiometric	1	0 to 360 programmable	Servo mount size 20	Solder pin, cable, miniature connector, terminal block
	**50A PBSL S2410**	Contactless, Hall	50	15 - 30 V	0 to 10 V DC	1	0 to 360 programmable	Servo mount size 20	Solder pin, cable, miniature connector, terminal block
	**50A PBSL S2442**	Contactless, Hall	50	15 - 30 V	4 to 20 mA	1	0 to 360 programmable	Servo mount size 20	Solder pin, cable, miniature connector, terminal block

		Technology	Housing Ø [mm]	Supply voltage [V]	Output signal	Number of outputs	Angle el. [°]	Mounting	Output Connection
	**50A PBSL S0505 2C**								
	**22I PBBL S05OC**	Contactless, Hall	22	5 V +/- 10%	Incremental 5 V Op.Col.	1	0 to 360 programmable	Bushing - 1 hole	Cable, terminal block
	**22I PBBL S24OC**	Contactless, Hall	22	9 - 30 V	Incremental 24 V Op.Col.	1	0 to 360 programmable	Bushing - 1 hole	Cable, terminal block
	**22I PBBL S05TTL**	Contactless, Hall	22	5 V +/- 10%	Incremental 5 V TTL	1	0 to 360 programmable	Bushing - 1 hole	Cable, terminal block
	**22I EPPF1 S05OC**	Contactless, Hall	22	5 V +/- 10%	Incremental 5 V Op.Col.	1	0 to 360 programmable	Flange - 2 screws	Cable
	**22I EPPF1 S24OC**	Contactless, Hall	22	9 - 30 V	Incremental 24 V Op.Col.	1	0 to 360 programmable	Flange - 2 screws	Cable
	**22I EPPF1 S05TTL**	Contactless, Hall	22	5 V +/- 10%	Incremental 5 V TTL	1	0 to 360 programmable	Flange - 2 screws	Cable
	**36I PBSL S05OC**	Contactless, Hall	36	5 V +/- 10%	Incremental 5 V Op.Col.	1	0 to 360 programmable	3 mounting screws	Solder pin, cable, miniature connector, terminal block

		Technology	Housing Ø [mm]	Supply voltage [V]	Output signal	Number of outputs	Angle el. [°]	Mounting	Output Connection
	**36I PBSL S24OC**	Contactless, Hall	36	9 - 30 V	Incremental 24 V Op.Col.	1	0 to 360 programmable	3 mounting screws	Solder pin, cable, miniature connector, terminal block
	**36I PBSL S05TTL 1024CW OCP**	Contactless, Hall	36	5 V +/- 10%	Incremental 5 V TTL	1	0 to 360 programmable	3 mounting screws	Solder pin, cable, miniature connector, terminal block
	**50I PBSL S05OC**	Contactless, Hall	50	5 V +/- 10%	Incremental 5 V Op.Col.	1	0 to 360 programmable	Servo mount size 20	Solder pin, cable, miniature connector, terminal block
	**50I PBSL S24OC**	Contactless, Hall	50	9 - 30 V	Incremental 24 V Op.Col.	1	0 to 360 programmable	Servo mount size 20	Solder pin, cable, miniature connector, terminal block
	**50I PBSL S05TTL**	Contactless, Hall	50	5 V +/- 10%	Incremental 5 V TTL	1	0 to 360 programmable	Servo mount size 20	Solder pin, cable, miniature connector, terminal block
	**22P PBBL 05SPI**	Contactless, Hall	22	5 V +/- 10%	Absolute SPI	1	0 to 360 programmable	Bushing - 1 hole	Cable, terminal block
	**22P PBBL 05SPI 2C**	Contactless, Hall	22	5 V +/- 10%	Absolute SPI	2	0 to 360 programmable	Bushing - 1 hole	Cable, terminal block
	**36P PBSL 05SPI**	Contactless, Hall	50	5 V +/- 10%	Absolute SPI	1	0 to 360 programmable	3 mounting screws	Solder pin, cable, miniature connector, terminal block

		Technology	Housing Ø [mm]	Supply voltage [V]	Output signal	Number of outputs	Angle el. [°]	Mounting	Output Connection
	**36P PBSL 05SPI 2**	Contactless, Hall	50	5 V +/- 10%	Absolute SPI	2	0 to 360 programmable	3 mounting screws	Solder pin, cable, miniature connector, terminal block
	**50P PBSL 05SPI**	Contactless, Hall	50	5 V +/- 10%	Absolute SPI	1	0 to 360 programmable	Servo mount size 20	Solder pin, cable, miniature connector, terminal block
	**50P PBSL 05SPI 2C**	Contactless, Hall	50	5 V +/- 10%	Absolute SPI	2	0 to 360 programmable	Servo mount size 20	Solder pin, cable, miniature connector, terminal block
	**22Y PBBL 05SSI**	Contactless, Hall	22	5 V +/- 10%	5 V SSI	1	0 to 360 programmable	Bushing - 1 hole	Cable, terminal block
	**22Y PBBL 24SSI**	Contactless, Hall	22	9 - 30 V	24 V SSI	1	0 to 360 programmable	Bushing - 1 hole	Cable, terminal block
	**36Y PBSL 05SSI**	Contactless, Hall	50	5 V +/- 10%	5 V SSI	1	0 to 360 programmable	3 mounting screws	Solder pin, cable, miniature connector, terminal block
	**36Y PBSL 24SSI**	Contactless, Hall	50	9 - 30 V	24 V SSI	1	0 to 360 programmable	3 mounting screws	Solder pin, cable, miniature connector, terminal block
	**50Y PBSL 05SSI**	Contactless, Hall	50	5 V +/- 10%	5 V SSI	1	0 to 360 programmable	Servo mount size 20	Solder pin, cable, miniature connector, terminal block

		Technology	Housing Ø [mm]	Supply voltage [V]	Output signal	Number of outputs	Angle el. [°]	Mounting	Output Connection
	**50Y PBSL 24SSI**	Contactless, Hall	50	9 - 30 V	24 V SSI	1	0 to 360 programmable	Servo mount size 20	Solder pin, cable, miniature connector, terminal block
	**22A PBB S0505**	Contactless, Hall	22	5 V +/- 10%	0 to 5 V DC Ratiometric	1	0 to 360 programmable	Bushing - 1 hole	Cable, terminal block
	**22A PBBF S0505**	Contactless, Hall	22	5 V +/- 10%	0 to 5 V DC Ratiometric	1	0 to 360 programmable	Bushing - 1 hole	Cable
	**22A PBBF S2410**	Contactless, Hall	22	15 - 30 V	0 to 10 V DC	1	0 to 360 programmable	Bushing - 1 hole	Cable
	**22A PBBF S2442**	Contactless, Hall	22	15 - 30 V	4 to 20 mA	1	0 to 360 programmable	Bushing - 1 hole	Cable
	**36A PBSF S0505**	Contactless, Hall	50	5 V +/- 10%	0 to 5 V DC ratiometric	1	0 to 360 programmable	3 mounting screws	Solder Pin
	**36A PBSF S2410**	Contactless, Hall	50	15-30 V	0 to 10 V DC	1	0 to 360 programmable	3 mounting screws	Solder Pin
	**36A PBSF S2442**	Contactless, Hall	50	15 - 30 V	4 to 20 mA	1	0 to 360 programmable	3 mounting screws	Solder Pin

		Technology	Housing Ø [mm]	Supply voltage [V]	Output signal	Number of outputs	Angle el. [°]	Mounting	Output Connection
	**CP-45F-10SX**	Resistive	45	0...15	0 to 100% Vin	1	0 to 3500	Servo Ø45	Solder Pin

Angst+Pfister
Sensors and Power

We are here for you. Addresses and Contacts.

Headquarter Switzerland:

Angst+Pfister Sensors and Power AG
Thurgauerstrasse 66
CH-8050 Zurich
Phone +41 44 877 35 00
sensorsandpower@angst-pfister.com

Office Germany:

Angst+Pfister Sensors and Power Deutschland GmbH
Edisonstraße 16
D-85716 Unterschleißheim
Phone +49 89 374 288 87 00
sensorsandpower.de@angst-pfister.com

Scan here and get an overview of personal contacts!

sensorsandpower.angst-pfister.com