
		Measuring range [mm]	Output signal	Linearity [± %FS]	Resolution [mm]	Supply voltage [V]	Dimension [mm]	Environment
	**LX-EP2**	250 to 1250	AB	0.35 bis 0.50	0.22 to 0.5	5	45 x 40 x 60	IP40
	**LX-PA**	50 to 120	Ratiometric voltage	1	infinite	0 to 30	45 x 46 x 60	IP40
	**LX-PA**	250 to 625	Ratiometric voltage	0.5	infinite	1 to 30	45 x 46 x 60	IP40
	**LX-PA**	750 to 1250	Ratiometric voltage	0.25	infinite	2 to 30	45 x 46 x 60	IP40
	**JX-PA**	50 to 120	Ratiometric voltage	1	infinite	3 to 30	57 x 86 x 79	IP52, IP65
	**JX-PA**	250 to 625	Ratiometric voltage	0.5	infinite	4 to 30	57 x 86 x 79	IP52, IP65
	**JX-PA**	750 to 2000	Ratiometric voltage	0.25	infinite	5 to 30	57 x 86 x 79	IP52, IP65
	**JX-P420**	50 to 120	4...20mA	1	infinite	9 to 35	57 x 86 x 79	IP52, IP65

		Measuring range [mm]	Output signal	Linearity [± %FS]	Resolution [mm]	Supply voltage [V]	Dimension [mm]	Environment
	**JX-P420**	250 to 625	4...20mA	0.5	infinite	9 to 35	57 x 86 x 79	IP52, IP65
	**JX-P420**	750 to 2000	4...20mA	0.25	infinite	9 to 35	57 x 86 x 79	IP52, IP65
	**PSX-F58-Mechanik**	1000 to 42500	Any (depend on external sensor)	0.05		12 to 30		IP65, IP67
	**PSX50**	50 to 1250	Ratiometric, 0...10V, 4...20mA	0.15	infinite	12 to 30		IP65, IP67
	**PSX50**	625 to 1250	ABI	0.01, 0.05	0.03	5 / 8 to 30		IP65, IP67
	**PSX80**	1000 to 3000	Ratiometric, 0...10V, 4...20mA	0.05, 0.1	infinite	12 to 30		IP65, IP67
	**PSX80**	1000 to 3000	ABI	0.01, 0.05	0.04	5 / 8 to 30		IP65, IP67
	**PSX80**	1000 to 3000	Bus absolute	0.05	12 bits	10 to 30		IP64

		Measuring range [mm]	Output signal	Linearity [± %FS]	Resolution [mm]	Supply voltage [V]	Dimension [mm]	Environment
	**PSX120**	3125 to 6000	Ratiometric, 0...10V, 4...20mA	0.05, 0.1	infinite	12 to 30		IP65, IP67
	**PSX120**	3125 to 6000	ABI	0.05	0.06	5 / 8 to 30		IP65, IP67
	**PSX120**	3125 to 6000	Bus absolute	0.05	12 bits	10 to 30		IP64
	**PMH120**	3000 to 6000	ratiometric, 4..20mA, 0...10V, CANOpen	0.1	limited by noise	10 to 30		IP64
	**PSX135**	6000 to 40000	Ratiometric, 0...10V, 4...20mA	0.05, 0.1	infinite	12 to 30		IP65, IP67
	**PSX135**	6000 to 40000	ABI	0.05	0.06	5 / 8 to 30		IP65, IP67
	**PA**	50 to 125	Ratiometric voltage	0.25	infinite	0 to 30	133 x 67 x 57	IP40
	**PA**	250 to 640	Ratiometric voltage	0.15	infinite	0 to 25	133 x 67 x 57	IP40

		Measuring range [mm]	Output signal	Linearity [± %FS]	Resolution [mm]	Supply voltage [V]	Dimension [mm]	Environment
	**PA**	750 to 1250	Ratiometric voltage	0.1	infinite	0 to 25	133 x 67 x 57	IP40
	**PA**	1500 to 2000	Ratiometric voltage	0.1	infinite	0 to 25	133 x 95 x 83	IP40
	**PB**	50 to 125	Bridge voltage	0.25	infinite	0 to 25	133 x 67 x 57	IP40
	**PB**	250 to 640	Bridge voltage	0.15	infinite	0 to 25	133 x 67 x 57	IP40
	**PB**	750 to 1250	Bridge voltage	0.1	infinite	0 to 25	133 x 67 x 57	IP40
	**PB**	1500 to 2000	Bridge voltage	0.1	infinite	0 to 25	133 x 95 x 83	IP40
	**P420**	50 to 125	4...20mA	0.25	infinite	9 to 35	133 x 67 x 57	IP40
	**P420**	250 to 640	4...20mA	0.15	infinite	9 to 35	133 x 67 x 57	IP40

		Measuring range [mm]	Output signal	Linearity [± %FS]	Resolution [mm]	Supply voltage [V]	Dimension [mm]	Environment
	**P420**	750 to 1250	4...20mA	0.1	infinite	9 to 35	133 x 67 x 57	IP40
	**P420**	1500 to 2000	4...20mA	0.1	infinite	9 to 35	133 x 95 x 83	IP40
	**P510**	50 to 125	0...5V, 0...10V	0.25	infinite	11 to 35	133 x 67 x 57	IP40
	**P510**	250 to 640	0...5V, 0...10V	0.15	infinite	11 to 35	133 x 67 x 57	IP40
	**P510**	750 to 1250	0...5V, 0...10V	0.1	infinite	11 to 35	133 x 67 x 57	IP40
	**P510**	1500 to 2000	0...5V, 0...10V	0.1	infinite	11 to 35	133 x 95 x 83	IP40
	**HX-PA**	50 to 150	Ratiometric voltage	0.25	infinite	0 to 30	121 x 74 x 74	IP65, IP68
	**HX-PA**	250 to 640	Ratiometric voltage	0.15	infinite	0 to 30	121 x 74 x 74	IP65, IP68

		Measuring range [mm]	Output signal	Linearity [± %FS]	Resolution [mm]	Supply voltage [V]	Dimension [mm]	Environment
	**HX-PA**	640 to 2000	Ratiometric voltage	0.1	infinite	0 to 30	121 x 74 x 74	IP65, IP68
	**HX-PA**	2500 to 50800	Ratiometric voltage	0.1	infinite	0 to 30	A x 155 x 144	IP65, IP68
	**HX-PB**	50 to 150	Bridge voltage	0.25	infinite	0 to 30	121 x 74 x 74	IP65, IP68
	**HX-PB**	250 to 640	Bridge voltage	0.15	infinite	0 to 30	121 x 74 x 74	IP65, IP68
	**HX-PB**	640 to 2000	Bridge voltage	0.1	infinite	0 to 30	121 x 74 x 74	IP65, IP68
	**HX-PB**	2500 to 50800	Bridge voltage	0.1	infinite	0 to 30	A x 155 x 144	IP65, IP68
	**HX-P420**	50 to 150	4...20mA	0.3	infinite	9 to 35	121 x 74 x 74	IP65, IP68
	**HX-P420**	250 to 640	4...20mA	0.2	infinite	9 to 35	121 x 74 x 74	IP65, IP68

		Measuring range [mm]	Output signal	Linearity [± %FS]	Resolution [mm]	Supply voltage [V]	Dimension [mm]	Environment
	**HX-P420**	640 to 2000	4...20mA	0.15	infinite	9 to 35	121 x 74 x 74	IP65, IP68
	**HX-P420**	2500 to 50800	4...20mA	0.15	infinite	9 to 35	A x 155 x 144	IP65, IP68
	**HX-P510**	50 to 150	0...5V, 0...10V	0.3	infinite	11 to 35	121 x 74 x 74	IP65, IP68
	**HX-P510**	250 to 640	0...5V, 0...10V	0.2	infinite	11 to 35	121 x 74 x 74	IP65, IP68
	**HX-P510**	640 to 2000	0...5V, 0...10V	0.15	infinite	11 to 35	121 x 74 x 74	IP65, IP68
	**HX-P510**	2500 to 50800	0...5V, 0...10V	0.15	infinite	11 to 35	A x 155 x 144	IP65, IP68
	**EP**	250 to 1250	AB, line driver	0.03	0.05 to 0.1	5	133 x 67 x 57	IP40
	**HX-EP**	250 to 2000	AB, line driver	0.03	0.05 to 0.16	5	121 x 74 x 74	IP65, IP68

		Measuring range [mm]	Output signal	Linearity [± %FS]	Resolution [mm]	Supply voltage [V]	Dimension [mm]	Environment
	**HX-EP**	2500 to 50800	AB, line driver	0.03	0.3	5	A x 155 x 144	IP65, IP68

Angst+Pfister
Sensors and Power

We are here for you. Addresses and Contacts.

Headquarter Switzerland:

Angst+Pfister Sensors and Power AG
Thurgauerstrasse 66
CH-8050 Zurich
Phone +41 44 877 35 00
sensorsandpower@angst-pfister.com

Office Germany:

Angst+Pfister Sensors and Power Deutschland GmbH
Edisonstraße 16
D-85716 Unterschleißheim
Phone +49 89 374 288 87 00
sensorsandpower.de@angst-pfister.com

Scan here and get an overview of personal contacts!

sensorsandpower.angst-pfister.com