



MICS-EK1 Metal Oxide Semiconductor Gas Sensor Evaluation Kit

Getting started quickly with SGX Metal Oxide Semi- conductor Gas Sensors

Simply attach the universal power supply, connect to a PC USB port and plug in one or two gas sensors. The SGX data logging and control software allows the performance of different sensors to be assessed and makes it easy to capture performance data.



INTRODUCTION

The SGX MICS-EK1 Gas Sensor Evaluation Kit will drive the SGX range of Metal Oxide Semiconductor gas sensors and automatically measure the sensor resistance as it changes with applied gas.

Sensors can be driven manually or automatically by sending simple commands through the USB interface to an on-board microcontroller. A comprehensive set of commands is provided for use with a terminal program such as HyperTerminal. Alternatively an easy-to-use control and data logging PC application is provided on CD which gives full functionality in a few mouse-clicks.

Two gas sensor sockets are provided on the PCB to allow use with two leaded devices. Surface mount adapter boards are also available separately. One adapter PCB will plug in to both sockets and can be fitted with either a single or dual surface mount gas sensor.

The heaters can be set to two levels. These are nominally preset to 43 mW and 76 mW by plug-in resistors but may be changed by the user to other values. The microprocessor monitors the sensor output resistance with automatic resistance range switching.

An expansion connector provides access to four configurable alarms (open collector), two analog outputs and four digital inputs. LEDs on the board mimic the status of each alarm. A JTAG header allows advanced users to upload their own software to the microcontroller (MSP430F2616) and make full use of the available interfaces.

A universal mains adapter is also supplied or the user may connect a 9 V power supply to the terminal block connector.

FEATURES

- For use with SGX Metal Oxide Semiconductor Gas Sensors
- Automatic measuring of sensor resistance changes
- Operates two 4-pin leaded sensors or one 10-pin surface mount sensor (single or dual) with additional adapter PCB
- USB interface to a Personal Computer (PC)
- Free PC application software for easy control and data logging
- Settable heater drive levels
- Automatic load resistor switching
- Four configurable alarm outputs
- Two configurable analog outputs
- Four digital inputs
- Ambient temperature monitoring
- Provision for humidity sensor (customer fit)
- Expansion header for additional applications
- JTAG header for user software upload
- Supplied with universal mains adapter
- Supplied with user manual on CD

ELECTRICAL DATA

Universal Mains Adapter

Input voltage	90 - 264 V ac
Input frequency	50 – 60 Hz
Adapters supplied	UK, Europe, USA, Australia
Output	9 V dc

PCB Interfaces

DC Supply Input

SK4	2.1 x 5.5 mm socket, centre positive
TB1	terminal block
Input voltage	9 V ± 10%
Input protection	Over-voltage and current, reverse voltage

Gas Sensor Sockets

SK1	Channel 1: 4-pin TO5
SK2	Channel 2: 4-pin TO5

An optional adapter PCB can be plugged into SK1 and SK2 to allow a single or dual surface mount sensor to be used.

Expansion Connector

PL2	2 x 10-pin 0.1" PCB header
-----	----------------------------

3V3 regulated	1	2	9 V unregulated
0 V	3	4	0 V
Input 1 (3V3 logic)	5	6	Output 1 (Open collector)
Input 2 (3V3 logic)	7	8	Output 2 (Open collector)
Input 3 (3V3 logic)	9	10	Output 3 (Open collector)
Input 4 (3V3 logic)	11	12	Output 4 (Open collector)
0V	13	14	Analog out 1 (0 - 2.048 V)
0V	15	16	Analog out 2 (0 - 2.048 V)
Spare RXD (3V3)	17	18	Spare TXD (3V3)
0V	19	20	Spare

JTAG Connector

PL1	2 x 7-pin 0.1" box header
-----	---------------------------

TDO	1	2	VCCO
TDI	3	4	VCCI
TMS	5	6	Unused
TCK	7	8	Unused
0 V	9	10	Unused
TRST	11	12	Unused
Unused	13	14	Unused

Microcontroller Reset

SW2	Push-button
-----	-------------

Indicators

D1 – D4	Green LEDs (ON = alarm asserted)
D5	Green LED (flash = PCB functional)

Control Switch

SW1 1-4	Control of heater modes and humidity sensing (see manual)
---------	---

Heater Control Resistors

RA, RB	High/low power – channel 1
RC, RD	High/low power – channel 2

USB

SK5	Mini-USB type B
-----	-----------------

MECHANICAL DATA

Dimensions

Mains adapter	72 x 45 x 29 mm
Evaluation kit PCB	130 x 55 mm
SMD adapter PCB	25 x 10 mm

ENVIRONMENTAL DATA

Operating Temperature Range

Mains adapter	Operating temperature: 0 to +40 °C Storage temperature: -25 to +85 °C Operating humidity: 10 to 90%
---------------	---

PCBs	Designed for operation and storage from -40 to +85 °C
------	---

Sensors	See individual sensor data sheets
---------	-----------------------------------

PERFORMANCE DATA

ADC resolution	12-bit
DAC resolution	12-bit
Resistance measurement accuracy (25 °C)	≤2% (75R to 6.5M) ≤5% (30R to 20M)
Resistance measurement resolution (25 °C)	<1% (output given to 4 significant digits)
Temp measurement accuracy	±2 °C (at 25 °C) ±3 °C (-25 to +85 °C)

RECOMMENDED PC SYSTEM

For Control and Data Logging Software

Processor	Pentium 4/M or equivalent
Operating system	Windows XP or Vista
Screen resolution	1024 x 768 pixels
RAM	1 GB
Disk space	1.6 GB

ORDERING INFORMATION

MICS-EK1

MICS Gas Sensor Evaluation Kit Contents:

- Evaluation PCB
- Universal Mains Adapter
- USB lead
- CD Containing Data Logging Software and User Manual

MICS-SMD-PCB5

MICS Surface Mount Adapter Kit Contents

- 5 x SMD Adapter PCBs

Note: The above kits do not include sensors. These must be ordered separately.

Headquarter Switzerland:
Angst+Pfister Sensors and Power AG

Thurgauerstrasse 66
CH-8050 Zurich
Phone +41 44 877 35 00
sensorsandpower@angst-pfister.com

Office Germany:
Angst+Pfister Sensors and Power
Deutschland GmbH
Edisonstraße 16
D-85716 Unterschleißheim
Phone +49 89 374 288 87 0
sensorsandpower.de@angst-pfister.com



We are here for you. Addresses and Contacts.

Sales Germany & Austria

Geometrical sensors
Other products

Kurt Stritzelberger
Phone +49 89 374 288 87 22
kurt.stritzelberger@angst-pfister.com

Pressure sensors
Other products

Gerhard Vetter
Phone +49 89 374 288 87 26
gerhard.vetter@angst-pfister.com

Gas sensors and modules

Peter Felder
Phone +41 44 877 35 05
peter.felder@angst-pfister.com

Sales Switzerland & Liechtenstein

Postcode 3000 – 9999

Basil Frei
Phone +41 44 877 35 18
basil.frei@angst-pfister.com

Postcode 1000 – 2999

Christian Mohrenstecher
Phone +41 76 444 57 93
christian.mohrenstecher@angst-pfister.com

Sales International Key Accounts

Peter Felder
Phone +41 44 877 35 05
peter.felder@angst-pfister.com

Sales Other Countries / Product Management

Pressure Sensors
Load Cells

Philipp Kistler
Phone +41 44 877 35 03
philipp.kistler@angst-pfister.com

Gas sensors
Gas sensor modules

Dr. Thomas Clausen
Phone +49 89 374 288 87 24
thomas.clausen@angst-pfister.com

Flow / Level / Medical products

Dr. Adriano Pittarelli
Phone +49 89 374 288 87 67
adriano.pittarelli@angst-pfister.com

Power supplies

Sebastiano Leggio
Phone +41 44 877 35 06
sebastiano.leggio@angst-pfister.com

Linear position sensors
Angle sensors

Eric Letsch
Phone +41 44 877 35 14
eric.letsch@angst-pfister.com

Accelerometers
Sensor elements

Christoph Kleye
Phone +49 89 374 288 87 61
christoph.kleye@angst-pfister.com

Drive technology
CH Postcode 5000 – 9999 / DE

Roman Homa
Phone +41 76 444 00 86
roman.homa@angst-pfister.com

Drive technology
CH Postcode 1000 – 4999 / AT / IT / FR

Christian Mohrenstecher
Phone +41 76 444 57 93
christian.mohrenstecher@angst-pfister.com

Harald Thomas
Phone +49 89 374 288 87 23
harald.thomas@angst-pfister.com